

Avide Design Oyster Yvette 90W(45+45) with RF Remote

Product code: ADO3S-YV-2.4G
Brand link:
ID: AB-190518
Company name: Armin Trade Kft.
Company address: Kossuth utca 22 2/4, 4024 Debrecen

QR code:
Date of issue: 2023-01-20
Page: 1/3

SPECIFICATIONS

EAN code: 5999097944289
Warranty: 3year(s)
Material: Acryl+Metal
Working temperature: -20 + 40°C
Packaging: 1/b 5/c 40/p
Certifications: CE

TECHNICAL DETAILS

Wattage: 90W
Voltage: 200-265V
Beam angle: 120°
Dimmability: Yes
Lumen output: 7 110lm
Color temperature: 5 000K
Lifetime: 30 000h
Type of LED: SMD2835
CRI: 80
IP standard: IP20

BOX PICTURE



Avide Design Oyster Yvette 90W(45+45) with RF Remote

Product code: ADO3S-YV-2.4G
Brand link:
ID: AB-190518
Company name: Armin Trade Kft.
Company address: Kossuth utca 22 2/4, 4024 Debrecen

QR code:
Date of issue: 2023-01-20
Page: 2/3

PRODUCT SIZE

Diameter: 520mm
Height: 55mm

CARDBOARD BOX

EAN: 5999097944289
Packaging: 1/b 5/c 40/p
Dimensions: 520mm x 570mm x 75mm
Net weight: 3 120g
Gross weight: 3 760g

CARTON

EAN: 5999097944296
Packaging: 1/b 5/c 40/p
Dimensions: 590mm x 400mm x 570mm
Net weight: 15.6kg
Gross weight: 18.8kg


PALLET EXAMPLE

Height:
Width: 120cm (std Euro pallet)
Mepth: 80cm (std Euro pallet)
Cartons per pallet: 8carton/pallet
Cartons per row:
Net weight: 124.8kg
Gross weight: 150.4kg

PRODUCT PICTURE



PRODUCT OUTLINE



Avide Design Oyster Yvette 90W(45+45) with RF Remote

Product code: ADO3S-YV-2.4G

Brand link:

QR code:

ID: AB-190518

Date of issue: 2023-01-20

Company name: Armin Trade Kft.

Company address: Kossuth utca 22 2/4, 4024 Debrecen

Page: 3/3

PRODUCT DESCRIPTION

The new Avide design oysters bring unique style to our home.

There are 3 lighting modes available for each model. The first and second modes use a combination of warm white and cold white LEDs to achieve different lighting effects, while the third mode uses a combination of warm white and cold white LEDs to create a natural white color temperature, doubling the power and brightness as well.

Before the very first use, the remote controller has to be paired with the lamp!

Pairing: Within 5 seconds of power ON, push the marked (WIFI signed) button once shortly. If the pairing was successful, the lamp will blink 3 times and the remote controller is ready to use.

Unpairing: Within 5 seconds of power ON, push the marked (WIFI signed) button 3 times shortly. If the unpairing was successful, the lamp will blink several times.

In addition to switching between modes, the product's RF remote controller also allows you to adjust the brightness and color temperature, and to activate the timer function: Press once for 5 minutes, press twice for 30 minutes and press three times for turn off the timer.

The product has a memory function, so the previously used mode and brightness will be active at the next time you turn it on.